

CONNECTION

ENCRYPTION UNIT

RADIO

For use with 406136-E ISSUE: F/RF BOARD and 406037-E ISSUE: F/RF BOARD

(3)	(+) SUPPLY INPUT	RED	PL10-9	SW Power
(9)	(-) SUPPLY INPUT	BLACK	PL10-7	GND
(11)	RX AUDIO INPUT	BLUE		OF E102-1 AND Pad "B" al PCB)
(1)	RX AUDIO OUTPUT	WHT/BLU	JUNCTION (OF C32 AND Pad "A"
(12)	TX AUDIO INPUT	GREEN	, –	B) WHT/BLU See Notes OF R284 ANDC253
(13)	TX AUDIO OUTPUT	WHT/GRN		OF C253 AND R285
(6)	PTT INPUT	YELLOW	PL10-1	B) WHT/GRN See Notes PTT
(7)	CLEAR/CYPHER	BROWN	SK1-7	
(10)	CODE #3	BLK/YEL	USER SELE	CT ST-20B ONLY
(4)	LED	WHT/ORG	IC103-1	
(5)	CODE #2	BLK/ORG	USER SELE	CT ST-20B ONLY
(8)	PA ENABLE	BLK/BRN	N/C	
(2)	CODE #1	VIOLET	USER SELE	CT ST-20B ONLY Rev: 4-10-00-

Rev: 4-10-00-

REMOVE C253 AND C32.

ADD A .01µf CAP (REMOVED C253) IN SERIES WITH THE WHT/GRN WIRE.

ADD A $1\mu F$ CAP (REMOVED C32) IN SERIES WITH THE WHT/BLU WIRE TO PAD LABELED "A". TO CAUSE THE UNIT TO GO IN AND OUT OF CIPHER DOUBLECLICK THE AUX BUTTON ON THE

R4= NOT USED R21= NOT USED R28= 1.1K R47= 1.1K

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

SmarTrunk Systems ● 23278 Berhardt Street. HAYWARD, CA. 94545 ● (510) 887-1950

FAX (510) 887-4011 • e-mail admin@smartrunk.com