

FOR USE WITH: Kenwood TKR-820(Burst Tone Access Repeater) APPROVAL DATE: 110CT88 BY: WDC

		Tone Access Repeater) APPROVAL DATE: 110CT88 BY: WDC
CONNECT TONE UNIT		RADIO
(+) SUPPLY	(RED) -	 CN1-1 SIG. UNIT SB
(-) SUPPLY	(BLACK) -	
TONE INPUT	(GREEN) -	 CN1-8 SIG. UNIT AFO
MONITOR/HOOK SWITCH	(BROWN) -	 (SEE NOTE 1 BELOW)
DECODE LATCHED	(WHT/ORG) -	 COL. Q7 DISPLAY UNIT KEY
DECODE MOMENTARY	(WHT/VIO)	NC
LAMP (-)	(BLK/ORG)	NC
SET	(WHITE)	
MODIFICATIONS TONE UNIT		RADIO
USER: JU1=B JU3=SHORT		1. ADD THE FOLLOWING CIRCUIT USED TO PROVIDE RESET AFTER LOSS OF CARRIER.
(Note!) While the circuit shown to the left has been used successfully it is recommended that the coil circuit of the relay be bufered with an NPN transistor to prevent variations in output power due to loading of Tx 8V supply. +12VDC CN8-5/\/\ 1200 ohm Relay coil		CN8-5 (Tx/Rx UNIT) TRANSMIT 8V
THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTIONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION.		

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE SELECTONE INC. • 3501 BREAKWATER AVE. HAYWARD, CA. 94545-1610 • (510) 781-0376

(800) 227-0376

• FAX (510) 781-5454 • E-Mail admin@selectone.com