

Selectone

ST-139 APPLICATION NOTE #1382

FOR USE WITH: MOTOROLA MAXAR, MAXAR 80, MOXY, & FLEXAR

APPROVAL DATE: 29JUL97S BY:RTS

CONNECTIONS			RADIO	
TONE UNIT				
Application Cable				
7	MONITOR	(BROWN)	J601-1	(J901-1 for MOXY)
10	P.T.T. (ENCODE EN.)	(BLK/YEL)	M	GRN/BRN
4	DECODE (-)	(WHT/ORG)	G	GREY
1	HI PASS FILTER OUT	(WHT/BLU)	F	YEL/BLU
11	HI PASS FILTER IN	(BLUE)	E	YEL/WHT
12	TONE INPUT	(GREEN)	D	WHT/RED
13	ENCODE OUTPUT	(WHT/GRN)	P	BRN/ORG
3	(+) SUPPLY	(RED)	C	RED/WHT
9	(-) SUPPLY	(BLACK)	T	BLACK
Wire #'s 2,5,6,& 8 are NOT used.			J601-2	(J901-2 for MOXY)

MODIFICATIONS		RADIO	
TONE UNIT			
USER: JU1=OPEN JU4=OPEN		Remove JU2 & verify that JU102 is installed. The radio wire colors are as noted on the Motorola component locator for P.L. installation.	
Splice a second length of BLACK wire to the existing BLACK wire to be used as a jumper.		The Motorola hang-up box requires two wires J601-1 & J601-2 (-) SUPPLY/GND.	

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

SELECTONE INC. • 3501 BREAKWATER AVE. HAYWARD, CA. 94545-1610 • (510) 781-0376
(800) 227-0376 • FAX (510) 781-5454 • E-Mail admin@selectone.com