

FOR USE WITH: MOTOROLA GP350 **APPROVAL DATE: 02MAY97S BY: RTS** 

## CONNECTION

## **ENCRYPTION UNIT**

**RADIO** 

(3)	(+) SUPPLY INPUT	RED	JUNCTION OF R460 AND CR403	
(9)	(-) SUPPLY INPUT	BLACK	P1-8	GND
(11)	RX AUDIO INPUT	BLUE	P1-7	RX AUDIO IN
(1)	RX AUDIO OUTPUT	WHT/BLU	P1-6	RX AUDIO OUT
(12)	TX AUDIO INPUT	GREEN	P1-5	TX AUDIO IN
(13)	TX AUDIO OUTPUT	WHT/GRN	P1-4	TX AUDIO OUT
(6)	PTT INPUT	YELLOW	NOT USED	
(10)	PTT OUTPUT	BLK/YEL	JUNCTION OF R451 AND R452	
(7)	CLEAR/CIPHER	BROWN	JUNCTION OF M600 AND C483	
(5)	cos	BLK/ORG	P1-13	AUDIO PA ENABLE
(8)	AMP ENABLE/SEC PTT	BLK/BRN	P1-11	PTT
(2)	RS-232 IN	VIOLET	JUNCTION OF Q408 AND R494	
(4)	RS-232 OUT	WHT/ORG	NOT USED	Revised 07MAY97R BY RTS

NOTES: REMOVE R455 AND R506. ADD A 51K RESISTOR IN SERIES WITH THE **BLK/YEL WIRE.** 

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE SELECTONE INC. • 3501 BREAKWATER AVE. HAYWARD, CA. 94545-1610 • (510) 781-0376

(800) 227-0376

• FAX (510) 781-5454 •

E-Mail admin@selectone.com