

FOR USE WITH: MOTOROLA RADIUS MOBILES APPROVAL DATE: 18SEP98S BY: RTS

CONNECTION

ENCRYPTION UNIT

RADIO

(3)	(+) SUPPLY INPUT	RED	J6-1	9.6V
(9)	(-) SUPPLY INPUT	BLACK	J6-11	GND
(11)	RX AUDIO INPUT	BLUE	JUNCTION	OF U552 AND C561
(1)	RX AUDIO OUTPUT	WHT/BLU	JUNCTION OF R562 AND C561	
(12)	TX AUDIO INPUT	GREEN	Q651 COLLECTOR	
(13)	TX AUDIO OUTPUT	WHT/GRN	JUNCTION OF C652 AND R655	
(6)	PTT INPUT	YELLOW	J6-4	T/R SHIFT
(7)	CLEAR/CYPHER	BROWN	S1103 FPC	
(4)	BEEP	WHT/ORG	U553 PIN 2	
(8)	PA ENABLE	BLK/BRN	Q509 COLLECTOR	
(2)	CODE SELECT #1	VIOLET	USER SELECT TO GROUND	
(5)	CODE SELECT #2	BLK/ORG	USER SELECT TO GROUND	
(10)	CODE SELECT #3	BLK/YEL	USER SELECT TO GROUND	

FOR THE RADIO: REMOVE C561 AND C652.

FOR ST-20B & ST-25B:

Install JU1 on the ST-20B ONLY.

ADD A 11k RESISTOR IN SERIES WITH THE WHT/ORG LEAD.

ADD A .0068µF CAP (REMOVED C652) IN SERIES WITH WHT/GRN WIRE.

ADD A .22µF CAP (REMOVED C561) IN SERIES WITH WHT/BLUE

IF THERE IS NOISE ON TX CHANGE C22 ON ST-020B/25B TO A 10 μF CAPICTOR.

Program: ST-025b for LED operation for off and TX alert tone for on.

Note: THIS APPLICATION OPERATES IN DOUBLE CLICK MODE USING THE AUDIO MUTE BUTTON.

Note: This application also applies to the model GM300.

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

SmarTrunk Systems, Inc. • 23278 Bernhardt Street Hayward, CA. 94545 • Phone: (510) 887-1950 Fax:(510) 887-4011 • Website: www.selectone.com • E-Mail: technicalsupport@smartrunk.com