

Selectone

ST-200 APPLICATION NOTE #2133

FOR USE WITH: **Motorola MCX 90/100**

APPROVAL DATE: 27JUN89 BY: WDC

=====

CONNECTIONS

TONE UNIT

RADIO

(+) SUPPLY	(RED)	----	SW A+
(-) SUPPLY	(BLACK)	----	GND
TONE INPUT	(GREEN)	----	P352-18
MONITOR/HOOK SWITCH	(BROWN)	----	COMMON PIN OF S801 (*)
DECODE LATCHED	(WHT/ORG)	----	P352-12
DECODE MOMENTARY	(WHT/VIO)	----	USER SUPPLIED HORN
LAMP (-)	(BLK/ORG)	----	USER SUPPLIED CALL LAMP
SET	(WHITE)	----	NOT USED

=====

MODIFICATIONS

TONE UNIT

RADIO

USER:		(*) REMOVE THE EXISTING WIRE FROM S801 COMMON.
REMOVE Q4 AND REPLACE WITH A 1N914 DIODE. ANODE TO BASE, CATHODE TO COLLECTOR.		
JU1=B		
JU3=OPEN		
FACTORY:		

=====

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE

SELECTONE INC. • 3501 BREAKWATER AVE. HAYWARD, CA. 94545-1610 • (510) 781-0376
(800) 227-0376 • FAX (510) 781-5454 • E-Mail admin@selectone.com