



Notes: The Decoder is Modified by adding a 100uf cap. from Out. 1 to ground. A 3.9K resistor from Out. 1 to regulated 8vdc. on the decoder board.

Remove both JU-1 & JU-2. also R-22.

Remove jumper between Pins 1 & r on rec. board.

APPLICATION PARTS

- 1- 3.9 K 1/4W resistor
- 1- 100uf 12v capacitor
- 2- Program Labels
- 2- Mounting Squares

SPECIAL NOTICE

WHEN MOUNTING THE TS-32 WITH A 90 DEGREE ANGLE BRACKET AGAINST THE PCB, BE SURE TO USE THE TWO FIBER SPACERS PROVIDED BETWEEN ANGLE BRACKET AND PCB. IF THIS IS NOT DONE, THE BRACKET WILL SHORT OUT FOILS ON THE PCB



Communications Specialists

426 W. Taft Ave., Orange, CA 92667
(714) 998-3021 (California) / (800) 854-0547