



NOTE: Filter hook-up (cut out) may not be necessary.

Pin 4 of audio amp squelch card

Base of Q2 on mike amp T/R switch card

Monitor Switch:
Open=monitor
Closed=tone receive

High side of volume or squelch control

+12vdc from on-off switch

APPLICATION PARTS
(not supplied)

- 1- 33k 1/4w resistor
- 1- 100k 1/4w " "
- 1- .1uf-12v capacitor
- 1- Set hardware & wires

SPECIAL NOTICE

WHEN MOUNTING THE TS-32 WITH A 90 DEGREE ANGLE BRACKET AGAINST THE PCB, BE SURE TO USE THE TWO FIBER SPACERS PROVIDED BETWEEN ANGLE BRACKET AND PCB. IF THIS IS NOT DONE, THE BRACKET WILL SHORT OUT FOILS ON THE PCB