

Selectone

ST-804A APPLICATION NOTE # 8213

FOR USE WITH : MOTOROLA GM-300

APPROVAL DATE: 30SEP99S/R BY: CPE

oo

CONNECTIONS

ANI UNIT

RADIO

aa

(3)	(+) SUPPLY INPUT	RED	J8-7	13.8V
(9)	(-) SUPPLY INPUT	BLACK	J8-12	GND
(11)	N/A	BLUE	N/C	
(1)	N/A	WHT/BLU	N/C	
(12)	ENI ACTIVATE INPUT	GREEN	N/C	
(13)	DTMF TONE OUTPUT	WHT/GRN	Q651-C	
(6)	PTT INPUT	YELLOW	J8-13	PTT
(10)	PTT OUTPUT	BLK/YEL	JUNC. R887 & VR804	
(7)	N/A	BROWN	N/C	
(4)	RS-232 OUT	WHT/ORG	N/C	
(5)	MIC MUTE OUTPUT	BLK/ORG	JUNC. Q652 & R849	
(8)	N/A	BLK/BRN	N/C	
(2)	RS-232 INPUT	VIOLET	N/C	

oo

NOTES: CUT TRACE BETWEEN J8-13 & VR804 IN RADIO.

THIS IS A RECOMMENDED INSTALLATION PROCEDURE FOR SELECTONE EQUIPMENT BASED ON THE BEST INFORMATION AVAILABLE TO US AT THE TIME OF PUBLICATION. SELECTONE ASSUMES NO RESPONSIBILITY FOR THE ACCURACY OF THE INFORMATION OR THE DAMAGE TO EQUIPMENT RESULTING FROM THE USE OF THIS PROCEDURE